

SANGEAN

A WORLD OF LISTENING

WR-2

Wooden Cabinet
Receiver



\$339.00 RRP

AUD\$ inclusive of GST

FM-Stereo-RDS / AM / Wooden Cabinet Table Top / Digital Tuning Receiver

- Wooden cabinet available in real wood veneer or piano gloss finish black.
- PLL Synthesized tuning system.
- RDS featuring clock time, alternative frequency, traffic information, station name, program type and EON (Enhancement of Network).
- Large easy to read multi-function LCD display.
- Clock and alarm (radio / buzzer).
- Rotary tuning and volume control.
- Rotary bass and treble control.
- 10 memory preset (FM5, MW5).
- 3 inch, 7 watt full range speaker with enlarged magnet.
- Bass compensation for rich bass.
- External F type FM antenna terminal.
- Detachable power Cord.
- Aux in socket.
- Record out socket.
- Stereo headphones socket.
- 9 - 15 Voltage power adaptor socket for vehicle power.
- Multi-function infrared remote control.

PK's Loop Antennas
www.amradioantennas.com
email: pkloops@bigpond.net.au
phone: 0412 302 939

	MODEL	WR-2	
TUNING	Type	PLL synthesizer	
	Memory Presets	FM x 5 / AM x 5	
	Rotary Tuning	Yes	
DISPLAY	Type	STN LCD	
	Size (mm)	89 x 55	
	Back light	Yes	
BAND	FM	Frequency MHz	87.5-108
		Stereo (Via Headphone)	Yes
	AM	RDS	PS / PI / CT / AF / TI / EON
		Frequency kHz	522-1629
CLOCK	Real time	Yes	
	Alarm Radio	Yes	
	Alarm Buzzer	Yes	
	Snooze	Yes	
	Sleep	Yes	
	Radio control	RDS-CT	
AUDIO OUTPUT	Tone control	Bass, Treble	
	Speaker unit	3 inch 8 ohm	
OUTPUT POWER	AC/DC IN (Speaker)	7 W (AC/DC)	
	Batteries (Speaker)		
	Earphones	5+5 mW	
POWER SUPPLY	AC	230 V 50Hz	
	DC IN	12 V DC 1A	
I/O SOCKET	DC in	Yes	
	AC in	Yes	
	Earphones	Yes	
	Line out	Yes	
	Ext. Antenna	FM	
	AUX in	Yes	
ACCESSORIES	Remote Control	Yes	
DIMENSIONS	W x H x D (mm)	240 x 115 x 183	
	Weight (g)	2568	

WR-2

Wooden Cabinet Receiver

